

Enclosed Alphanumeric Supplement

Range: 1F100–1F1FF

This file contains an excerpt from the character code tables and list of character names for

The Unicode Standard, Version 17.0 BETA REVIEW DRAFT

This file may be changed at any time without notice to reflect errata, or other updates to the Unicode Standard.

See <https://www.unicode.org/errata/> for an up-to-date list of errata.

See <https://www.unicode.org/charts/> for access to a complete list of the latest character code charts. See <https://www.unicode.org/charts/PDF/Unicode-17.0/> for charts showing only the characters added in Unicode 17.0. See <https://www.unicode.org/Public/17.0.0/charts/> for a complete archived file of character code charts for Unicode 17.0. See <https://www.unicode.org/charts/About.html#Conventions> for conventions used in these code charts, and other general information.

Disclaimer

These charts are provided as the online reference to the character contents of the Unicode Standard, Version 17.0 but do not provide all the information needed to fully support individual scripts using the Unicode Standard. For a complete understanding of the use of the characters contained in this file, please consult the appropriate sections of The Unicode Standard, Version 17.0, online at <https://www.unicode.org/versions/Unicode17.0.0/>, as well as the Unicode Standard Annexes, the other Unicode Technical Reports and Standards, and the Unicode Character Database, which are available online.

See <https://www.unicode.org/ucd/> and <https://www.unicode.org/reports/>

A thorough understanding of the information contained in these additional sources is required for a successful implementation.

Fonts

The shapes of the reference glyphs used in these code charts are not prescriptive. Considerable variation is to be expected in actual fonts.

See <https://www.unicode.org/charts/fonts.html> for a list.

Terms of Use

© 1991–2025 Unicode, Inc. This publication is protected by copyright, and permission must be obtained from Unicode, Inc. prior to any reproduction, modification, or other use not permitted by the Terms of Use (<https://www.unicode.org/copyright.html>). Specifically, you may make copies of this publication and may annotate and translate it solely for personal or internal business purposes and not for public distribution, provided that any such permitted copies and modifications fully reproduce all copyright and other legal notices contained in the original. You may not make copies of or modifications to this publication for public distribution, or incorporate it in whole or in part into any product or publication without the express written permission of Unicode.

The Unicode Consortium specifically grants ISO a license to produce such code charts with their associated character names list to show the repertoire of characters for that standard, as a normatively referenced, integral part of that standard.

Unicode uses most fonts under restricted license from the original font owner. You may not extract, copy, modify, or distribute fonts or font data from any Unicode Products, including this publication, without license from the font owner.

Use of all Unicode Products, including this publication, is governed by the Unicode Terms of Use

(<https://www.unicode.org/copyright.html>). The authors, contributors, and publishers have taken care in the preparation of this publication, but make no express or implied representation or warranty of any kind and assume no responsibility or liability for errors or omissions or for consequential or incidental damages that may arise therefrom. This publication is provided “AS-IS” without charge as a convenience to users.

Unicode and the Unicode Logo are registered trademarks of Unicode, Inc., in the United States and other countries.

	1F10	1F11	1F12	1F13	1F14	1F15	1F16	1F17	1F18	1F19	1F1A	1F1B	1F1C	1F1D	1F1E	1F1F
0	0. 1F100	(A) 1F110	(Q) 1F120	A 1F130	Q 1F140	A 1F150	Q 1F160	A 1F170	Q 1F180	DJ 1F190	5.1 1F1A0					K 1F1F0
1	0, 1F101	(B) 1F111	(R) 1F121	B 1F131	R 1F141	B 1F151	R 1F161	B 1F171	R 1F181	CL 1F191	7.1 1F1A1					L 1F1F1
2	1, 1F102	(C) 1F112	(S) 1F122	C 1F132	S 1F142	C 1F152	S 1F162	C 1F172	S 1F182	COOL 1F192	22.2 1F1A2					M 1F1F2
3	2, 1F103	(D) 1F113	(T) 1F123	D 1F133	T 1F143	D 1F153	T 1F163	D 1F173	T 1F183	FREE 1F193	60P 1F1A3					N 1F1F3
4	3, 1F104	(E) 1F114	(U) 1F124	E 1F134	U 1F144	E 1F154	U 1F164	E 1F174	U 1F184	ID 1F194	120P 1F1A4					O 1F1F4
5	4, 1F105	(F) 1F115	(V) 1F125	F 1F135	V 1F145	F 1F155	V 1F165	F 1F175	V 1F185	NEW 1F195	d 1F1A5					P 1F1F5
6	5, 1F106	(G) 1F116	(W) 1F126	G 1F136	W 1F146	G 1F156	W 1F166	G 1F176	W 1F186	NG 1F196	HC 1F1A6				A 1F1E6	Q 1F1F6
7	6, 1F107	(H) 1F117	(X) 1F127	H 1F137	X 1F147	H 1F157	X 1F167	H 1F177	X 1F187	OK 1F197	HDR 1F1A7				B 1F1E7	R 1F1F7
8	7, 1F108	(I) 1F118	(Y) 1F128	I 1F138	Y 1F148	I 1F158	Y 1F168	I 1F178	Y 1F188	SOS 1F198	Hi-Res 1F1A8				C 1F1E8	S 1F1F8
9	8, 1F109	(J) 1F119	(Z) 1F129	J 1F139	Z 1F149	J 1F159	Z 1F169	J 1F179	Z 1F189	UP! 1F199	Loss less 1F1A9				D 1F1E9	T 1F1F9
A	9, 1F10A	(K) 1F11A	(S) 1F12A	K 1F13A	HV 1F14A	K 1F15A	MC 1F16A	K 1F17A	P 1F18A	VS 1F19A	SHV 1F1AA				E 1F1EA	U 1F1FA
B	⓪ 1F10B	(L) 1F11B	(C) 1F12B	L 1F13B	MV 1F14B	L 1F15B	MD 1F16B	L 1F17B	IC 1F18B	3D 1F19B	UHD 1F1AB				F 1F1EB	V 1F1FB
C	⓪ 1F10C	(M) 1F11C	(R) 1F12C	M 1F13C	SD 1F14C	M 1F15C	MR 1F16C	M 1F17C	PA 1F18C	2nd Scr 1F19C	VOD 1F1AC				G 1F1EC	W 1F1FC
D	⓪ 1F10D	(N) 1F11D	(CD) 1F12D	N 1F13D	SS 1F14D	N 1F15D	CC 1F16D	N 1F17D	SA 1F18D	2K 1F19D	M 1F1AD				H 1F1ED	X 1F1FD
E	⓪ 1F10E	(O) 1F11E	(Wz) 1F12E	O 1F13E	PPV 1F14E	O 1F15E	⓪ 1F16E	O 1F17E	AB 1F18E	4K 1F19E					I 1F1EE	Y 1F1FE
F	⓪ 1F10F	(P) 1F11F	⓪ 1F12F	P 1F13F	WC 1F14F	P 1F15F	⓪ 1F16F	P 1F17F	WC 1F18F	8K 1F19F					J 1F1EF	Z 1F1FF

Number with full stop

This symbol completes the set of numbers with full stop starting at 2488.

1F100 0. DIGIT ZERO FULL STOP
≈ 0030 0 002E .

Numbers with comma

1F101 0, DIGIT ZERO COMMA
≈ 0030 0 002C ,
1F102 1, DIGIT ONE COMMA
≈ 0031 1 002C ,
1F103 2, DIGIT TWO COMMA
≈ 0032 2 002C ,
1F104 3, DIGIT THREE COMMA
≈ 0033 3 002C ,
1F105 4, DIGIT FOUR COMMA
≈ 0034 4 002C ,
1F106 5, DIGIT FIVE COMMA
≈ 0035 5 002C ,
1F107 6, DIGIT SIX COMMA
≈ 0036 6 002C ,
1F108 7, DIGIT SEVEN COMMA
≈ 0037 7 002C ,
1F109 8, DIGIT EIGHT COMMA
≈ 0038 8 002C ,
1F10A 9, DIGIT NINE COMMA
≈ 0039 9 002C ,

Circled sans-serif digits

These digits complement the sans-serif digit sets in the Dingbat block ranges 2780-2789 and 278A-2793.

1F10B ① DINGBAT CIRCLED SANS-SERIF DIGIT ZERO
1F10C ② DINGBAT NEGATIVE CIRCLED SANS-SERIF DIGIT ZERO

Creative Commons symbols

Part of a Creative Commons symbol set also including 229C, 1F16D, 1F16E, and 1F16F.

1F10D ④ CIRCLED ZERO WITH SLASH
= no rights reserved
1F10E ⑤ CIRCLED ANTICLOCKWISE ARROW
= share alike
1F10F ⑥ CIRCLED DOLLAR SIGN WITH OVERLAID BACKSLASH
= non commercial

Parenthesized Latin letters

This set provides uppercase versions of the set starting at 249C. Parenthesized Latin letters do not have case mappings.

1F110 (A) PARENTHESIZED LATIN CAPITAL LETTER A
≈ 0028 (0041 A 0029)
1F111 (B) PARENTHESIZED LATIN CAPITAL LETTER B
≈ 0028 (0042 B 0029)
1F112 (C) PARENTHESIZED LATIN CAPITAL LETTER C
≈ 0028 (0043 C 0029)
1F113 (D) PARENTHESIZED LATIN CAPITAL LETTER D
≈ 0028 (0044 D 0029)
1F114 (E) PARENTHESIZED LATIN CAPITAL LETTER E
≈ 0028 (0045 E 0029)
1F115 (F) PARENTHESIZED LATIN CAPITAL LETTER F
≈ 0028 (0046 F 0029)
1F116 (G) PARENTHESIZED LATIN CAPITAL LETTER G
≈ 0028 (0047 G 0029)

1F117 (H) PARENTHESIZED LATIN CAPITAL LETTER H
≈ 0028 (0048 H 0029)
1F118 (I) PARENTHESIZED LATIN CAPITAL LETTER I
≈ 0028 (0049 I 0029)
1F119 (J) PARENTHESIZED LATIN CAPITAL LETTER J
≈ 0028 (004A J 0029)
1F11A (K) PARENTHESIZED LATIN CAPITAL LETTER K
≈ 0028 (004B K 0029)
1F11B (L) PARENTHESIZED LATIN CAPITAL LETTER L
≈ 0028 (004C L 0029)
1F11C (M) PARENTHESIZED LATIN CAPITAL LETTER M
≈ 0028 (004D M 0029)
1F11D (N) PARENTHESIZED LATIN CAPITAL LETTER N
≈ 0028 (004E N 0029)
1F11E (O) PARENTHESIZED LATIN CAPITAL LETTER O
≈ 0028 (004F O 0029)
1F11F (P) PARENTHESIZED LATIN CAPITAL LETTER P
≈ 0028 (0050 P 0029)
1F120 (Q) PARENTHESIZED LATIN CAPITAL LETTER Q
≈ 0028 (0051 Q 0029)
1F121 (R) PARENTHESIZED LATIN CAPITAL LETTER R
≈ 0028 (0052 R 0029)
1F122 (S) PARENTHESIZED LATIN CAPITAL LETTER S
≈ 0028 (0053 S 0029)
1F123 (T) PARENTHESIZED LATIN CAPITAL LETTER T
≈ 0028 (0054 T 0029)
1F124 (U) PARENTHESIZED LATIN CAPITAL LETTER U
≈ 0028 (0055 U 0029)
1F125 (V) PARENTHESIZED LATIN CAPITAL LETTER V
≈ 0028 (0056 V 0029)
1F126 (W) PARENTHESIZED LATIN CAPITAL LETTER W
≈ 0028 (0057 W 0029)
1F127 (X) PARENTHESIZED LATIN CAPITAL LETTER X
≈ 0028 (0058 X 0029)
1F128 (Y) PARENTHESIZED LATIN CAPITAL LETTER Y
≈ 0028 (0059 Y 0029)
1F129 (Z) PARENTHESIZED LATIN CAPITAL LETTER Z
≈ 0028 (005A Z 0029)

Latin letter with tortoise shell brackets

1F12A [S] TORTOISE SHELL BRACKETED LATIN CAPITAL LETTER S
• used in baseball scoring
≈ 3014 [0053 S 3015]

Circled italic Latin letters

1F12B © CIRCLED ITALIC LATIN CAPITAL LETTER C
= compact disc, single disc record
≈ <circle> 0043 C
1F12C ® CIRCLED ITALIC LATIN CAPITAL LETTER R
= disc record
≈ <circle> 0052 R

Circled Latin letters or letter sequences

1F12D © CIRCLED CD
→ 33C5 cd square cd
≈ <circle> 0043 C 0044 D
1F12E ® CIRCLED WZ
• from the German term "Warenzeichen"
• indicate a trademarked term without making a legal claim of trademark status
• decomposition is anomalous, as the usual glyph shows a capital W and a small z
→ 2122 ™ trade mark sign
≈ <circle> 0057 W 005A Z

- 1F12F © COPYLEFT SYMBOL
 → 00A9 © copyright sign
 → 2183 ㊀ roman numeral reversed one hundred

Squared Latin letters

- 1F130 A SQUARED LATIN CAPITAL LETTER A
 = Anreisetag (day of arrival)
 ≈ <square> 0041 A
- 1F131 B SQUARED LATIN CAPITAL LETTER B
 = bank
 = b-mode stereo compression broadcasting service (ARIB STD B24)
 ≈ <square> 0042 B
- 1F132 C SQUARED LATIN CAPITAL LETTER C
 ≈ <square> 0043 C
- 1F133 D SQUARED LATIN CAPITAL LETTER D
 ≈ <square> 0044 D
- 1F134 E SQUARED LATIN CAPITAL LETTER E
 ≈ <square> 0045 E
- 1F135 F SQUARED LATIN CAPITAL LETTER F
 ≈ <square> 0046 F
- 1F136 G SQUARED LATIN CAPITAL LETTER G
 ≈ <square> 0047 G
- 1F137 H SQUARED LATIN CAPITAL LETTER H
 ≈ <square> 0048 H
- 1F138 I SQUARED LATIN CAPITAL LETTER I
 ≈ <square> 0049 I
- 1F139 J SQUARED LATIN CAPITAL LETTER J
 ≈ <square> 004A J
- 1F13A K SQUARED LATIN CAPITAL LETTER K
 ≈ <square> 004B K
- 1F13B L SQUARED LATIN CAPITAL LETTER L
 ≈ <square> 004C L
- 1F13C M SQUARED LATIN CAPITAL LETTER M
 ≈ <square> 004D M
- 1F13D N SQUARED LATIN CAPITAL LETTER N
 = news (ARIB STD B24)
 ≈ <square> 004E N
- 1F13E O SQUARED LATIN CAPITAL LETTER O
 ≈ <square> 004F O
- 1F13F P SQUARED LATIN CAPITAL LETTER P
 = progressive broadcasting (ARIB STD B24)
 ≈ <square> 0050 P
- 1F140 Q SQUARED LATIN CAPITAL LETTER Q
 ≈ <square> 0051 Q
- 1F141 R SQUARED LATIN CAPITAL LETTER R
 ≈ <square> 0052 R
- 1F142 S SQUARED LATIN CAPITAL LETTER S
 = stereo broadcasting service (ARIB STD B24)
 ≈ <square> 0053 S
- 1F143 T SQUARED LATIN CAPITAL LETTER T
 = tobacconist
 ≈ <square> 0054 T
- 1F144 U SQUARED LATIN CAPITAL LETTER U
 ≈ <square> 0055 U
- 1F145 V SQUARED LATIN CAPITAL LETTER V
 ≈ <square> 0056 V
- 1F146 W SQUARED LATIN CAPITAL LETTER W
 = wide-format 16:9 broadcasting service (ARIB STD B24)
 ≈ <square> 0057 W
- 1F147 X SQUARED LATIN CAPITAL LETTER X
 ≈ <square> 0058 X

- 1F148 Y SQUARED LATIN CAPITAL LETTER Y
 ≈ <square> 0059 Y
- 1F149 Z SQUARED LATIN CAPITAL LETTER Z
 ≈ <square> 005A Z
- 1F14A HV SQUARED HV
 = hdtv
 ≈ <square> 0048 H 0056 V
- 1F14B MV SQUARED MV
 = multi-view television
 ≈ <square> 004D M 0056 V
- 1F14C SD SQUARED SD
 = sdtv
 ≈ <square> 0053 S 0044 D
- 1F14D SS SQUARED SS
 = surround stereo broadcasting service
 ≈ <square> 0053 S 0053 S
- 1F14E PPV SQUARED PPV
 = pay-per-view
 ≈ <square> 0050 P 0050 P 0056 V
- 1F14F WC SQUARED WC
 = water closet, public toilet
 → 1F6BE ㊂ water closet
 ≈ <square> 0057 W 0043 C

White on black circled Latin letters

- 1F150 A NEGATIVE CIRCLED LATIN CAPITAL LETTER A
 = airport
- 1F151 B NEGATIVE CIRCLED LATIN CAPITAL LETTER B
- 1F152 C NEGATIVE CIRCLED LATIN CAPITAL LETTER C
- 1F153 D NEGATIVE CIRCLED LATIN CAPITAL LETTER D
- 1F154 E NEGATIVE CIRCLED LATIN CAPITAL LETTER E
- 1F155 F NEGATIVE CIRCLED LATIN CAPITAL LETTER F
 = ferry
- 1F156 G NEGATIVE CIRCLED LATIN CAPITAL LETTER G
- 1F157 H NEGATIVE CIRCLED LATIN CAPITAL LETTER H
 = hotel (ARIB STD B24)
- 1F158 I NEGATIVE CIRCLED LATIN CAPITAL LETTER I
- 1F159 J NEGATIVE CIRCLED LATIN CAPITAL LETTER J
- 1F15A K NEGATIVE CIRCLED LATIN CAPITAL LETTER K
 = Kurort (spa)
 → 2668 ㊂ hot springs
- 1F15B L NEGATIVE CIRCLED LATIN CAPITAL LETTER L
 = light rail
 → 1F688 ㊂ light rail
- 1F15C M NEGATIVE CIRCLED LATIN CAPITAL LETTER M
 = metro
 → 1F687 ㊂ metro
- 1F15D N NEGATIVE CIRCLED LATIN CAPITAL LETTER N
- 1F15E O NEGATIVE CIRCLED LATIN CAPITAL LETTER O
- 1F15F P NEGATIVE CIRCLED LATIN CAPITAL LETTER P
 = parking space (ARIB STD B24)
- 1F160 Q NEGATIVE CIRCLED LATIN CAPITAL LETTER Q
- 1F161 R NEGATIVE CIRCLED LATIN CAPITAL LETTER R
 = Raststätte (rest stop)
- 1F162 S NEGATIVE CIRCLED LATIN CAPITAL LETTER S
 = Stadtbahn (metropolitan railway)
- 1F163 T NEGATIVE CIRCLED LATIN CAPITAL LETTER T
 = Tankstelle (petrol station)
 → 26FD ㊂ fuel pump
- 1F164 U NEGATIVE CIRCLED LATIN CAPITAL LETTER U
 = underground rail
 → 1F687 ㊂ metro
- 1F165 V NEGATIVE CIRCLED LATIN CAPITAL LETTER V
- 1F166 W NEGATIVE CIRCLED LATIN CAPITAL LETTER W

- 1F167  NEGATIVE CIRCLED LATIN CAPITAL LETTER X
 1F168  NEGATIVE CIRCLED LATIN CAPITAL LETTER Y
 1F169  NEGATIVE CIRCLED LATIN CAPITAL LETTER Z

Raised squared Latin sequences

- 1F16A  **MC** RAISED MC SIGN
 = marque de commerce
 • used in Canada
 → 2122 TM trade mark sign
 ≈ <sup> 004D **M** 0043 **C**
 1F16B  **MD** RAISED MD SIGN
 = marque déposée
 • used in Canada
 → 00AE [®] registered sign
 ≈ <sup> 004D **M** 0044 **D**
 1F16C  **MR** RAISED MR SIGN
 = marca registrada
 • used primarily in Spanish and Portuguese speaking communities to indicate a registered trademark
 → 00AE [®] registered sign
 ≈ <sup> 004D **M** 0052 **R**

Creative Commons symbols

- 1F16D  **CC** CIRCLED CC
 = Creative Commons license
 → 229C [⊕] circled equals
 1F16E  **C** CIRCLED C WITH OVERLAID BACKSLASH
 = public domain
 1F16F  **Ⓘ** CIRCLED HUMAN FIGURE
 = attribution, credit

White on black squared Latin letters

The square edges may be slightly rounded.

- 1F170  **A** NEGATIVE SQUARED LATIN CAPITAL LETTER A
 = blood type A
 1F171  **B** NEGATIVE SQUARED LATIN CAPITAL LETTER B
 = blood type B
 1F172  **C** NEGATIVE SQUARED LATIN CAPITAL LETTER C
 = centre, city centre
 1F173  **D** NEGATIVE SQUARED LATIN CAPITAL LETTER D
 1F174  **E** NEGATIVE SQUARED LATIN CAPITAL LETTER E
 1F175  **F** NEGATIVE SQUARED LATIN CAPITAL LETTER F
 = Feuerwache (fire department)
 1F176  **G** NEGATIVE SQUARED LATIN CAPITAL LETTER G
 1F177  **H** NEGATIVE SQUARED LATIN CAPITAL LETTER H
 = Haltestelle (bus stop)
 → 1F68F ^ℹ bus stop
 1F178  **I** NEGATIVE SQUARED LATIN CAPITAL LETTER I
 1F179  **J** NEGATIVE SQUARED LATIN CAPITAL LETTER J
 = junction (ARIB STD B24)
 1F17A  **K** NEGATIVE SQUARED LATIN CAPITAL LETTER K
 1F17B  **L** NEGATIVE SQUARED LATIN CAPITAL LETTER L
 = leisure center (ARIB STD B24)
 1F17C  **M** NEGATIVE SQUARED LATIN CAPITAL LETTER M
 = museum, cultural center (ARIB STD B24)
 1F17D  **N** NEGATIVE SQUARED LATIN CAPITAL LETTER N
 1F17E  **O** NEGATIVE SQUARED LATIN CAPITAL LETTER O
 = blood type O
 1F17F  **P** NEGATIVE SQUARED LATIN CAPITAL LETTER P
 = parking space empty-full (ARIB STD B24)
 1F180  **Q** NEGATIVE SQUARED LATIN CAPITAL LETTER Q
 1F181  **R** NEGATIVE SQUARED LATIN CAPITAL LETTER R
 1F182  **S** NEGATIVE SQUARED LATIN CAPITAL LETTER S
 1F183  **T** NEGATIVE SQUARED LATIN CAPITAL LETTER T

- 1F184  **U** NEGATIVE SQUARED LATIN CAPITAL LETTER U
 1F185  **V** NEGATIVE SQUARED LATIN CAPITAL LETTER V
 1F186  **W** NEGATIVE SQUARED LATIN CAPITAL LETTER W
 1F187  **X** NEGATIVE SQUARED LATIN CAPITAL LETTER X
 1F188  **Y** NEGATIVE SQUARED LATIN CAPITAL LETTER Y
 1F189  **Z** NEGATIVE SQUARED LATIN CAPITAL LETTER Z
 1F18A  **P** CROSSED NEGATIVE SQUARED LATIN CAPITAL LETTER P
 = parking space closed
 1F18B  **IC** NEGATIVE SQUARED IC
 = interchange, ramp
 1F18C  **PA** NEGATIVE SQUARED PA
 = parking area
 1F18D  **SA** NEGATIVE SQUARED SA
 = service area
 1F18E  **AB** NEGATIVE SQUARED AB
 = blood type AB
 1F18F  **WC** NEGATIVE SQUARED WC
 = water closet, public toilet
 → 1F6BE [🚻] water closet

Squared Latin letter sequences

- 1F190  **DJ** SQUARE DJ
 = disc jockey
 ≈ <square> 0044 **D** 004A **J**
 1F191  **CL** SQUARED CL
 = clear
 1F192  **COOL** SQUARED COOL
 1F193  **FREE** SQUARED FREE
 = free postage
 1F194  **ID** SQUARED ID
 = identification, ID
 1F195  **NEW** SQUARED NEW
 1F196  **NG** SQUARED NG
 = no good
 1F197  **OK** SQUARED OK
 1F198  **SOS** SQUARED SOS
 = search, hunt for missing person
 1F199  **UP!** SQUARED UP WITH EXCLAMATION MARK
 = new information, update
 1F19A  **VS** SQUARED VS
 = versus

Squared Latin letter sequences from ARIB STD B62

- 1F19B  **3D** SQUARED THREE D
 1F19C  **2nd Ser** SQUARED SECOND SCREEN
 1F19D  **2K** SQUARED TWO K
 1F19E  **4K** SQUARED FOUR K
 1F19F  **8K** SQUARED EIGHT K
 1F1A0  **5.1** SQUARED FIVE POINT ONE
 • denotes 5.1-channel surround sound
 1F1A1  **7.1** SQUARED SEVEN POINT ONE
 • denotes 7.1-channel surround sound
 1F1A2  **22.2** SQUARED TWENTY-TWO POINT TWO
 • denotes 22.2-channel surround sound
 1F1A3  **60P** SQUARED SIXTY P
 • denotes 60Hz frame rate with progressive scanning
 1F1A4  **120P** SQUARED ONE HUNDRED TWENTY P
 • denotes 120Hz frame rate with progressive scanning
 1F1A5  **d** SQUARED LATIN SMALL LETTER D
 = data
 1F1A6  **HC** SQUARED HC
 = hybrid cast

- 1F1A7  SQUARED HDR
= high dynamic range
- 1F1A8  SQUARED HI-RES
= high resolution
- 1F1A9  SQUARED LOSSLESS
- 1F1AA  SQUARED SHV
= super high vision
- 1F1AB  SQUARED UHD
= ultra-high definition
- 1F1AC  SQUARED VOD
= video on demand

Miscellaneous symbol

- 1F1AD  MASK WORK SYMBOL
- indicates intellectual property protection for integrated circuit layouts
 - 00A9 © copyright sign
 - 24C2 ™ circled latin capital letter m

Regional indicator symbols

These characters can be used in pairs to represent regional codes. In some emoji implementations, certain pairs may be recognized and displayed by alternate means; for instance, an implementation might recognize F + R and display this combination with a symbol representing the flag of France.

- 1F1E6  REGIONAL INDICATOR SYMBOL LETTER A
- 1F1E7  REGIONAL INDICATOR SYMBOL LETTER B
- 1F1E8  REGIONAL INDICATOR SYMBOL LETTER C
- 1F1E9  REGIONAL INDICATOR SYMBOL LETTER D
- 1F1EA  REGIONAL INDICATOR SYMBOL LETTER E
- 1F1EB  REGIONAL INDICATOR SYMBOL LETTER F
- 1F1EC  REGIONAL INDICATOR SYMBOL LETTER G
- 1F1ED  REGIONAL INDICATOR SYMBOL LETTER H
- 1F1EE  REGIONAL INDICATOR SYMBOL LETTER I
- 1F1EF  REGIONAL INDICATOR SYMBOL LETTER J
- 1F1F0  REGIONAL INDICATOR SYMBOL LETTER K
- 1F1F1  REGIONAL INDICATOR SYMBOL LETTER L
- 1F1F2  REGIONAL INDICATOR SYMBOL LETTER M
- 1F1F3  REGIONAL INDICATOR SYMBOL LETTER N
- 1F1F4  REGIONAL INDICATOR SYMBOL LETTER O
- 1F1F5  REGIONAL INDICATOR SYMBOL LETTER P
- 1F1F6  REGIONAL INDICATOR SYMBOL LETTER Q
- 1F1F7  REGIONAL INDICATOR SYMBOL LETTER R
- 1F1F8  REGIONAL INDICATOR SYMBOL LETTER S
- 1F1F9  REGIONAL INDICATOR SYMBOL LETTER T
- 1F1FA  REGIONAL INDICATOR SYMBOL LETTER U
- 1F1FB  REGIONAL INDICATOR SYMBOL LETTER V
- 1F1FC  REGIONAL INDICATOR SYMBOL LETTER W
- 1F1FD  REGIONAL INDICATOR SYMBOL LETTER X
- 1F1FE  REGIONAL INDICATOR SYMBOL LETTER Y
- 1F1FF  REGIONAL INDICATOR SYMBOL LETTER Z